


J-Link™ Technology
www.segger.com




www.nordicsemi.com

400092
0202RUBR



Bat1



- P0.07 (SCL)
- P0.30 (SDA)
- P0.00 (AREF)
- GND

- P0.29 (13)
- P0.28 (12)
- P0.25 (11)
- P0.24 (10)
- P0.23 (9)
- P0.20 (8)

p10

- P0.19 (7)
- P0.18 (6)
- P0.17 (5)
- P0.16 (4)
- P0.15 (3)
- P0.14 (2)
- P0.13 (1)

- P0.12 (ARDUINO D0)

p9

- P0.11
- P0.10
- P0.09
- P0.08
- P0.27
- P0.26
- P0.22
- P0.21

p12

GPIO	Function	Short	HW
P0.08	RTS	SB13/22	IF MCU SB2x SB1x GPIO PIN
P0.09	TXD	SB14/23	
P0.10	CTS	SB15/24	
P0.11	RXD	SB16/25	
P0.26	XL2	SB1 SB3	PIN GPIO T I
P0.27	XL1	SB2 SB4	


- VDD
- VDD
- RESET
- VDD
- 5V
- GND
- GND
- N.C.

p7

nRF Pin	Short	HW
SWDIO/nRESET	SB17	nRF PIN

- P0.01 (A0)
- P0.02 (A1)
- P0.03 (A2)
- P0.04 (A3)
- P0.05 (A4)
- P0.06 (A5)

p8



GPIO	Function	Short	HW	I/O EXPANDER
P0.17	Button 1		* H	* (-T-) DETECT
P0.18	Button 2			
P0.19	Button 3			
P0.20	Button 4			
P0.21	LED 1	SB5	VDD LED PIN	EXP 12C nRF
P0.22	LED 2	SB6		
P0.23	LED 3	SB7		
P0.24	LED 4	SB8		